



FV34BSA Yarland

Class A push-pull amplifier





An affordable Yarland tube amplifier with power!
 This is the Yarland to combine with speakers that are a bit less efficient. It offers the grip and power of a push pull design and offers a remarkably smooth presentation.

YARLAND

Zebra wood front*



*Real wood, so real appearance may differ.

Push Pull EL34 integrated amplifier

| | |
|--------------------|--|
| Power: | 30 Watt per channel |
| Power tubes: | 4× Shuguang EL34 B |
| Pretubes: | 2× Beijing 6N3 (5670) |
| Rectifier tube: | 1× 12AX7 |
| Bandwidth: | 10 Hz – 37 kHz – 1.0 dB |
| Signal to noise: | 89 dB |
| Inputs: | 3 (CD, AUX & LINE) |
| Load: | 4 and 8 Ohm loudspeaker taps |
| Bias: | fixed, adjustable from the outside |
| Coupling Cap: | ClarityCap SA |
| Power: | 230 Volts version 50/60 Hz |
| Power consumption: | < 150 Watts |
| Dimensions W×H×D: | 32×15×28 cm |
| Weight: | 17 kilogram |
| Warranty: | 2 year on the amplifier, 6 months on the tubes |

More information? Visit www.yarland.eu or www.capsandcoils.com